

SPECIFICATION

TECHNICAL DATA SHEET

4000W Outdoor Power Supply



CET-DY4000

1 > General Performance

- ◆ 4000W Portable Power Station
- ◆ Support Wi-Fi, Bluetooth & Voice control
- ◆ Battery:AC charging;solar charging;charging with EV charging station.Battery capacity: 3600W.This 4000W power station can use two or more extra battery for expansion
- ◆ Output Ports:AC Output Port,USB Output Port,USB-C Output Port,Car port.
- ◆ UPS function:When after the power grid is suddenly cut off,this product can automatically switch to the battery power supply mode of this product within 15ms.It is recommended to use only one device during use rather than multiple devices at

2 > Product Specification


Output		
AC Output	Rated Voltage	100-120V
	Rated Power	3600W
	Peak Power	6000W
AC Output	Rated Voltage	220-240V
	Rated Power	4000W
	Peak Power	6000W
Car port output	Rated Voltage	12V
	Rated Current	18A
	Power	120W (MAX)
USB-A (Output*2)	Rated Voltage- Current	5V-2.4A
	Power	12W (MAX)
USB-A (Output*2)	Rated Voltage- Current	5V-3A,5V-2A,12V-1.5A
	Power	36W (MAX)
USB-C (Output*1)	Rated Voltage- Current	5V/9V/15V-3A,20V-5A
	Power	200W(MAX)
Rv Port output	Rated Current	30A(MAX)
Input		
AC/EV Charging Station Input	Rated Voltage	100-120V
	Rated Current	15A
	Power	1500W(MAX)
AC/EV Charging Station Input	Rated Voltage	220-240V
	Rated Current	16A
	Power	2000W(MAX)
Solar Energy	Rated Voltage	12-150V
	Rated Current	40A
	Power	2000W(MAX)
AC/EV Charging Stations/Batter	Power	3500W(MAX)
Battery		
Rated Capacity		3600Wh
Battery Cell Type		Lithium iron phosphate (LiFePO4)
Protection system	High temperature protection,low temperature protection,over discharge protection,over charge protection,overload protection,short circuit protection,over current protection	
General		
Storage Environment		-14°F-104°F
Working Temperature		-14°F-104°F
Product Size		540* 490*300mm
Product Net weight		48kg
Certificates		1.CE 2.UL 3.PSE 4.UKCA 5.FCC 6.RoHS 7.UN38.3 8.MSDS

SPECIFICATION

TECHNICAL DATA SHEET

3 > Product Introduction

3.1 Appearance introduction



1. Power On/Off
2. 2000W Max EV Input
3. Parallel Input
4. USB-A Output *4
5. RV Port 30A
6. AC Output *4(US 20A Max)
7. Car Port
8. LED Display
9. USB-C Output *2(PD100W Max)
10. AC Input
11. Solar Input XT60 2000W Max(12-150v)

3.2 Introduction of display icon



1. Home icon
2. Settings icon
3. Data icon
4. Log icon
5. Time icon
6. AC charging icon
7. Solar charging real-time charging p 14. WIFI icon
8. AC load icon
9. DC load icon
10. AC switch icon
11. DC switch icon
12. Power icon
13. Bluetooth icon

4 > Packing Information

4000W Portable Power Station*1
MC4 TO XT60 charging cable *1



AC Charging Cable *1
User Manual and warranty card * 1



Item	Quantity	G.W / CTN	Carton Size
CET-DY4000	1 PCS/CTN	52.55kg	76.4*41.4*59.5cm

5 > Warranty (1-Year-Limited)

The manufacturer's warranty is void under the following circumstances but not limited to:

- ◆ The appearance of the product is damaged after use;
- ◆ Product performance failure caused by human factors.

- ◆ Disassembly and repair by non staff members without permission;
- ◆ Damage caused by irresistible factors such as natural disasters, lightning and accidents.

6 > Company Information

Camel Electronic Technology Co., Ltd.

Add: No. 40, Dajinzhong Road, Baitun District, Guangzhou City, Guangdong Province, CN 551040

Tel&WhatsApp: +86-13822168739

Email: info@camelet.com

Linkedin:linkedin.com/in/文墨-5624a1ba

Official Website: <http://www.camelet.com>



Camel Electronic Technology Co., Ltd

For reference only, the actual product specifications prevail.